

## **KANAVARASTERI 6,8 GHz**

### **Taajuusjako DRS 140/6800, DRS 155/6800 ja DRS 2x34/6800 radiolinkeille**

RECOMMENDATION ITU-R F.384

CEPT/ERC/REC T/R 14-02

<b>40 MHz kanava</b>	<b>taajuus MHz (a)</b>	<b>taajuus MHz (b)</b>
1	6460	6800
2	6500	6840
3	6540	6880
4	6580	6920
5	6620	6960
6	6660	7000
7	6700	7040
8	6740	7080

### **Taajuusjako DRS 360/6800 radiolinkeille**

RECOMMENDATION ITU-R F.384

CEPT/ERC/RECOMMENDATION T/R 14-02

<b>60 MHz kanava</b>	<b>taajuus MHz (a)</b>	<b>taajuus MHz (b)</b>
A1	6475	6815
A2	6535	6875
A3	6595	6935
A4	6655	6995
A5	6715	7055