

## Channel grid 23 GHz

### Frequency allocation for DRS 34/23000 radio relay links

CEPT/ERC/REC T/R 13-02

<b>28 MHz channel</b>	<b>frequency MHz (a)</b>	<b>frequency MHz (b)</b>
A1	22190	23198
A2	22218	23226
A3	22246	23254
A4	22274	23282
A5	22302	23310
A6	22330	23338
A7	22358	23366
A8	22386	23394
A9	22414	23422

### Frequency allocation for DRS 2x8/23000 radio relay links

CEPT/ERC/REC T/R 13-02

<b>14 MHz channel</b>	<b>frequency MHz (a)</b>	<b>frequency MHz (b)</b>	
B3	22435	23443	
B4	22449	23457	
B5	22463	23471	
B6	22477	23485	
B7	22491	23499	
B8	22505	23513	B8 temporary use

### Frequency allocation for DRS 8/23000 radio relay links

CEPT/ERC/REC T/R 13-02

<b>7 MHz channel</b>	<b>frequency MHz (a)</b>	<b>frequency MHz (b)</b>
D1	22515,5	23523,5
D2	22522,5	23530,5
D3	22529,5	23537,5
D4	22536,5	23544,5
D5	22543,5	23551,5
D6	22550,5	23558,5
D7	22557,5	23565,5
D8	22564,5	23572,5
D9	22571,5	23579,5

### Frequency allocation DRS 155/23000 radio relay links

CEPT/ERC/RECOMMENDATION T/R 13-02

<b>56 MHz channel</b>	<b>frequency MHz (a)</b>	<b>frequency MHz (b)</b>
E1	22078	23086
E2	22134	23142