

Channel grid 15 GHz

Frequency allocation for DRS 8/15000 and 2x8/15000 radio relay links

ITU-R F.636

| 14 MHz channel | frequency MHz (a) | frequency MHz (b) | |
|---------------------------|------------------------------|------------------------------|------------------|
| A1 | 14515 | 15243 | |
| A2 | 14529 | 15257 | |
| A3 | 14543 | 15271 | |
| A4 | 14557 | 15285 | |
| A5 | 14571 | 15299 | |
| A6 | 14585 | 15313 | |
| A7 | 14599 | 15327 | |
| A8 | 14613 | 15341 | A8 temporary use |

| 14 MHz channel | frequency MHz (a) | frequency MHz (b) | |
|---------------------------|------------------------------|------------------------------|----------------------------------------|
| B1 | 14627 | 14935 | B1 - B3 transmitter power 300 mW |
| B2 | 14641 | 14949 | |
| B3 | 14655 | 14963 | |
| B4 | 14669 | 14977 | |
| B5 | 14683 | 14991 | |
| B6 | 14697 | 15005 | |
| B7 | 14711 | 15019 | |
| B8 | 14725 | 15033 | |
| B9 | 14739 | 15047 | |
| B10 | 14753 | 15061 | |
| B11 | 14767 | 15075 | |
| B12 | 14781 | 15089 | |
| B13 | 14795 | 15103 | |
| B14 | 14809 | 15117 | |
| B15 | 14823 | 15131 | |
| B16 | 14837 | 15145 | |
| B17 | 14851 | 15159 | |
| B18 | 14865 | 15173 | |
| B19 | 14879 | 15187 | |
| B20 | 14893 | 15201 | |
| B21 | 14907 | 15215 | |
| B22 | 14921 | 15229 | B22 temporary use |